



# Adore StyleLine BT Connexx Slim-RIC BT Charging Case

.....  
User Guide  
.....

[www.rexton.com](http://www.rexton.com)

**REXTON** 

# Content

Welcome	4
Intended use	5
Your hearing instruments	6
Instrument type	6
Getting to know your hearing instruments	7
Components and names	7
Hearing programs	9
Features	9
Daily use	10
Charging	10
Turning on and off hearing instruments	14
Switching to standby mode	15
Inserting and removing the hearing instruments	16
Adjusting the volume	20
Changing the hearing program	20
Charging the internal battery of your charger	21
Checking the battery capacity of your charger	23
Special listening situations	24
On the phone	24
Audio streaming with iPhone	25
Airplane mode for hearing instruments	25
Frequently asked questions	26

Maintenance and care	28
Hearing instruments	28
Ear pieces	30
Charger	32
Professional maintenance	33
Important safety information for hearing instruments and charger	34
Safety information on lithium-ion rechargeable batteries	34
Safety information for hearing instruments	35
Safety information for charger	36
Further information	40
Accessories	40
Operating, transport and storage conditions for hearing instruments and charger	40
Disposal information	41
Symbols	42
Troubleshooting	44
Country-specific information	45
Important information	46
Conformance information for charger	46
Service and warranty	47

## Welcome

Thank you for choosing our hearing instruments to accompany you through everyday life. Like anything new, it may take you a little time to become familiar with them.

This guide, along with support from your Hearing Care Professional, will help you understand the advantages and greater quality of life your hearing instruments offer.

To receive the most benefit from your hearing instruments, it is recommended that you wear them every day, all day. This will help you get adjusted to them.



### **CAUTION**

It is important to read this user guide and the safety manual thoroughly and completely. Follow the safety information to avoid damage or injury.



Before using your hearing instruments for the first time, fully charge them. Follow the instructions in the charger's user guide.

## Intended use

Hearing instruments are intended to improve the hearing of hearing impaired persons. Diagnosis and prescription of a hearing instrument must be performed by hearing health specialists, e.g. acousticians, audiologists or ENT doctors.

The charger is intended to charge our specific hearing instruments with built-in power cells (lithium-ion rechargeable batteries).

Use the hearing instruments and accessories only as described in the respective user guides.

## Your hearing instruments



This user guide describes optional features that your hearing instruments may or may not have. Ask your Hearing Care Professional to indicate the features that are valid for your hearing instruments.

### Instrument type

Your hearing instruments are a RIC (Receiver-in-Canal) model. The receiver is placed within the ear canal and connected to the instrument via a receiver cable. The instruments are not intended for children under the age of 3 years or persons with a developmental age of under 3 years.

A power cell (lithium-ion rechargeable battery) is permanently built into your hearing instrument. This enables easy charging with our charger.

The wireless functionality enables advanced audiological features and synchronization between your two hearing instruments.

Your hearing instruments feature Bluetooth® low energy\* technology allowing for easy data exchange with your smartphone, and for seamless audio streaming with your iPhone\*\*.

\* The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc., and any use of such marks by the legal manufacturer of this product is under licenses. Other trademarks and trade names are those of their respective owners.

\*\* iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.

## Getting to know your hearing instruments


Your hearing instruments have no controls.

If you want to adjust the volume or switch hearing programs manually, you can ask your Hearing Care Professional about a remote control option.

### Components and names



- 
- |                  |   |
|------------------|---|
| 1 Ear piece      | 4 Microphone openings                             |
| 2 Receiver       | 5 Charging contacts                               |
| 3 Receiver cable | 6 Side indicator<br>(R = right ear, L = left ear) |
-



1 Lid

2 Charging slots





3 Status LEDs

4 Button

5 USB port for power supply

6 USB power cable

You can use the following standard ear pieces:

Standard ear pieces	Size
<input type="checkbox"/>  Click Sleeve (vented or closed)	
<input type="checkbox"/>  Click Dome™ single (open or closed)	
<input type="checkbox"/>  Click Dome semi-open	
<input type="checkbox"/>  Click Dome double	



You can easily exchange the standard ear pieces.  
Read more in section "Maintenance and care".

## Hearing programs

---

1

---

2

---

3

---

4

---

5

---

6

---

Read more in section "Changing the hearing program".

## Features



The **Tinnitus Function** generates a sound to distract you from your tinnitus.

# Daily use

## Charging


### How you can use the charger

You can use your charger in three different ways.

#### Charging via electrical outlet


When the charger is plugged in, it charges the hearing instruments (if they are placed in the charger) and it charges the integrated battery at the same time.

The front status LED permanently shows the charging status of the charger. The hearing instruments' charging status is shown when opening the lid and/or pushing the button.



#### Mobile charging

When you are mobile with no electrical outlet available, you can still charge your hearing instruments. Energy is fed from the charger's integrated battery into your hearing instruments. The charger must be turned on to do so.




The charging status of charger and hearing instruments is shown by pushing the button or opening the lid.

## Safekeeping

When no charging is needed, turn the charger off and safely store your hearing instruments inside of it. The charger can only be turned off when it is **not** plugged in.

No charging status can be displayed.



## Turning the charger on or off


When the charger is connected to an electrical outlet, it is automatically turned on and cannot be turned off.

During mobile charging, press and hold the button for 5 seconds to turn the charger on or off.

- When the charger turns on, the status of the hearing instruments and the status of the charger's internal battery are displayed for 7 seconds.
- When the charger turns off, the front LED flashes green ■■ for approximately 15 seconds.

## Charging hearing instruments

- ▶ Place the right hearing instrument in the charging slot marked with an "R", and the left hearing instrument in the charging slot marked with an "L".
- ▶ Stow the ear pieces nicely.
- ▶ Close the charger's lid (optional).
- ▶ The hearing instruments are automatically turned off and start charging. The charging status is shown for 7 seconds.



If the status LEDs do not light up when you insert the hearing instruments, check the following:

- The hearing instruments are not correctly placed. Push them slightly into their charging slots or close the charger's lid.
- The charger is not connected to an electrical outlet and it is off. Press and hold the button for 5 seconds to turn on the charger.
- The charger's internal battery is too low for mobile charging. Connect the charger to an electrical outlet.




## NOTICE




If you put a hearing instrument in the wrong charging slot, the receiver cable may be damaged when closing the charger's lid.

### Charging status of hearing instruments

The **LED** next to the hearing instrument indicates the charging status of the hearing instrument. Note that the status is only displayed immediately after putting the hearing instruments in the charger, when you briefly press the button or when you open the lid.



When the charger is off, no status is displayed at all.

LED	Status description
	Pulsing green Hearing instrument is being charged.
	Green Hearing instrument is fully charged.
	LED is off No hearing instrument is in the charger, hearing instrument is not placed correctly, or charger is off.

### Low power indication of the hearing instruments

You will hear an alert signal to indicate the power cell is running low. The signal will be repeated every 20 minutes. Depending on the usage of your hearing instruments, you have approximately 1.5 hours to charge your hearing instruments before they stop working.

### Turning on and off hearing instruments

You have the following options to turn your hearing instruments on or off.

- ▶ Turning on: Take the instruments out of the charger. The startup melody is played in your hearing instruments. The **default** volume and hearing program are set.
- ▶ Turning off: Place the hearing instruments in the charger.

Note that the charger must be on.

## Switching to standby mode

Via remote control, you can switch your hearing instruments to standby mode. This mutes the hearing instruments. When you leave standby mode, the **previously** used volume and hearing program are set.

Note:

- In standby mode, the hearing instruments are **not** turned off completely. They draw some power.  
Therefore we recommend to use standby mode only for a short period of time.
- If you want to leave standby mode, but the remote control is not at hand: Turn your hearing instruments off and on again (by shortly placing them in the charger until one or more LEDs light up). Wait until the startup melody is played in your hearing instruments. This may take several seconds. Note that the **default** volume and hearing program are set.

## Inserting and removing the hearing instruments

Your hearing instruments have been fine-tuned for your right and left ear. Letters indicate the side:


- R = right ear
- L = left ear



Inserting a hearing instrument:

- ▶ For Click Sleeves, take care that the bend of the Click Sleeve is in line with the bend of the receiver cable.

Correct:



Incorrect:






- ▶ Hold the receiver cable at the bend closer to the ear piece.
- ▶ Carefully push the ear piece in the ear canal ①.
- ▶ Twist it slightly until it sits well.

Open and close your mouth to avoid accumulation of air in the ear canal.

- ▶ Lift the hearing instrument and slide it over the top of your ear ②.



### CAUTION

Risk of injury!

- ▶ Insert the ear piece carefully and not too deeply into the ear.



- It may be helpful to insert the **right** hearing instrument with the **right** hand and the **left** hearing instrument with the **left** hand.
- If you have problems inserting the ear piece, use the other hand to gently pull your earlobe downwards. This opens the ear canal and eases insertion of the ear piece.


The optional retention strand helps to securely retain the ear piece in your ear. To position the retention strand:

- ▶ Bend the retention strand and position it carefully into the bottom of the bowl of your ear (refer to the picture).



Removing a hearing instrument:

- ▶ Lift the hearing instrument and slide it over the top of your ear ①.



- ▶ Grip the receiver in the ear canal with two fingers and pull it carefully out ②.

Do not pull the receiver cable.



#### **CAUTION**

Risk of injury!

- ▶ In very rare cases the ear piece could remain in your ear when removing the hearing instrument. If this happens, have the ear piece removed by a medical professional.

Clean and dry your hearing instruments after usage.  
Read more in section "Maintenance and care".

## Adjusting the volume

Your hearing instruments automatically adjust the volume to the listening situation.

- ▶ If you prefer manual volume adjustment, use a remote control option.

An optional signal can indicate the volume change.

## Changing the hearing program

Depending on the listening situation, your hearing instruments automatically adjust their sound.

Your hearing instruments may also have several hearing programs which allow you to change the sound, if needed. An optional signal tone can indicate the program change.

- ▶ To change the hearing program manually, use a remote control option.

Refer to section "Hearing programs" for a list of your hearing programs.

The default volume is applied.


## Charging the internal battery of your charger



### NOTICE

Use of incompatible parts poses a risk of malfunction.

- ▶ Use only the USB power cable that is provided with the charger.
- ▶ Ensure your electrical plug complies with the requirements. Refer to the section "Requirements for the electrical plug".
- ▶ Connect the micro-USB side of the USB power cable to the charger ①.
- ▶ Connect the other side of the USB power cable to a suitable electrical plug ②.







The internal battery starts charging. When hearing instruments are inserted, they start charging as well. The charging status of the charger is shown permanently.

## Charging status of your charger

The **front LED** indicates the charging status of the charger and its internal battery.

While the internal battery is being charged, the charging status is indicated as follows:



LED	Status description
	Pulsing green Internal battery is being charged.
	Green Charger is fully charged.
	LED is off Cooling phase. Charging is resumed when the device has cooled down.

For an overview of the hearing instruments' charging status, refer to the section "Charging hearing instruments".




## Checking the battery capacity of your charger

To check whether the charger's internal battery has enough capacity to fully charge your hearing instruments when you are mobile:



- ▶ Disconnect the charger from the electrical outlet.
- ▶ Briefly press the button.

The **front LED** indicates the status of the charger's internal battery for 7 seconds.

LED	Status description
	Green Internal battery has enough capacity to fully charge two hearing instruments.
	Orange Internal battery does <b>not</b> have enough capacity to fully charge two hearing instruments.
	Blinking orange Internal charger battery empty. Charging of hearing instruments is not possible.

If the status LED does not light up when you press the button, check the following:

- The charger is off. Press and hold the button for 5 seconds to turn on the charger.
- The charger's internal battery is too low to display the status. Connect the charger to an electrical outlet, wait several minutes and try again.

## Special listening situations

### On the phone

When you are on the phone, hold the telephone receiver slightly above your ear. The hearing instrument and telephone receiver have to be aligned. Turn the receiver slightly so that the ear is not completely covered.



### Telephone program

You may prefer a certain volume when using the phone. Ask your Hearing Care Professional to configure a telephone program.

- ▶ Switch to the telephone program whenever you are on the phone.

If a telephone program is configured for your hearing instruments, it is listed in section "Hearing programs".



## Audio streaming with iPhone

Your hearing instruments are **Made for iPhone** hearing instruments. This means you can get phone calls and listen to music from your iPhone directly into your hearing instruments.

For more information about compatible iOS devices, pairing, audio streaming and other useful functions, contact your Hearing Care Professional.

## Airplane mode for hearing instruments

In areas where the use of Bluetooth technology is not allowed (e.g. on some airplanes), you can activate the airplane mode. This turns Bluetooth in your hearing instruments off temporarily. The hearing instruments still work without Bluetooth, however direct audio streaming will not be possible and other functions will not be available.

- ▶ To activate or deactivate the airplane mode, use the smartphone app.

An alert tone indicates when airplane mode is activated or deactivated.

## Frequently asked questions

You may have some questions on how to best charge your hearing instruments. Read the questions and answers below. If you have more questions, your Hearing Care Professional will help you.



### **Why do my hearing instruments not turn on when I take them out of the charger?**

Check the following:

- The charger is off. Press and hold the button for 5 seconds to turn on the charger. Refer to the section "Turning the charger on or off".
- The charger's internal battery is too low. Connect the charger to an electrical outlet.

Now take your hearing instruments out of the charger.



### **How can I turn off my hearing instruments without charging them?**

- ▶ Place the hearing instruments in the charger. Ensure that they are inserted correctly (status LEDs light up). The hearing instruments are automatically turned off and start charging.
- ▶ Disconnect the charger from the electrical outlet.
- ▶ Press and hold the button for 5 seconds to turn off the charger. Charging stops.



### **What should I pay attention to when charging?**

The hearing instruments and charger must be clean and dry. Observe the operation conditions in section "Operating, transport, and storage conditions".

Avoid charging at high temperatures, as this can shorten the life span and capacity of the power cell.

If you use the charger in a very warm environment, note that it will stop charging if the charger's temperature exceeds 42 °C (107 °F) in order to cool down. The front LED will stop flashing orange during the cooling phase. Charging resumes automatically after the device has cooled down. Do not touch the hearing instruments until the front LED resumes blinking, the hearing instruments may be hot.

## Maintenance and care

To prevent damage it is important that you take care of your hearing instruments and follow a few basic rules, which will soon become a part of your daily routine.

### Hearing instruments

#### Cleaning

Your hearing instruments have a protective coating. However, if not cleaned regularly you may damage the hearing instruments or cause personal injury.

- ▶ Clean your hearing instruments daily with a soft, dry tissue.
- ▶ Never use running water or immerse the devices in water.
- ▶ Never apply pressure while cleaning.
- ▶ Ask your Hearing Care Professional for recommended cleaning products, special care sets, or more information on how to keep your hearing instruments in good condition.



#### Drying

Use conventional products to dry your hearing instruments. Ask your Hearing Care Professional for recommended drying products and for individual instructions on when to dry your hearing instruments.

## Storage

- Short-term storage (up to several days): Turn off your hearing instruments by placing them in the charger.

The charger must be on. If the charger is not on and you place your hearing instruments in the charger, the hearing instruments are **not** turned off.

Note that when you turn off the hearing instruments via a remote control or smartphone app, the hearing instruments are **not** turned off completely. They are in standby-mode and still draw some power.

- Long-term storage (weeks, months, ...): First, fully charge your hearing instruments. Leave them in the charger and turn the charger off.

The hearing instruments are also turned off.

We recommend using drying products while storing the hearing instruments.

At 6 month intervals you will have to charge the hearing instruments to avoid an unrecoverable deep-discharge of the power cell. Deep-discharged power cells cannot be charged anymore and they have to be replaced. We recommend recharging more frequently than 6 month intervals.

Observe the storage conditions in section "Operating, transport and storage conditions".

## Ear pieces


### Cleaning

Cerumen (ear wax) may accumulate on the ear pieces. This may affect sound quality. Clean the ear pieces daily.

For all types of ear pieces:


- ▶ Clean the ear piece right after removal with a soft and dry tissue.

This prevents that cerumen becomes dry and hard.



For Click Domes or Click Sleeves:

- ▶ Squeeze the tip of the ear piece.




## Exchanging

Exchange standard ear pieces approximately every three months. Replace them sooner if you notice cracks or other changes. The procedure for exchanging standard ear pieces depends on the type of ear piece. In section "Components and names", your Hearing Care Professional has marked your type of ear piece.

### Exchanging Click Domes

- ▶ To remove the old Click Dome, use the removal tool or follow the instructions on the packaging of the Click Domes. Be careful not to pull the receiver cable.



The removal tool is available as an accessory.

- ▶ Take particular care that the new Click Dome clicks noticeable in place.
- ▶ Check the firm fit of the new Click Dome.



## Exchanging Click Sleeves

- ▶ Turn the Click Sleeve inside out.
- ▶ Grasp the Click Sleeve and the receiver (not the receiver cable) with your fingers and pull the Click Sleeve off.
- ▶ Take particular care that the new Click Sleeve clicks noticeably in place.



## Charger

### Cleaning



#### **NOTICE**

Risk of injuries caused by electric shock!

- ▶ If cleaning is required, disconnect the charger from the power supply.
- ▶ Clean the charger with a soft, dry tissue.
- ▶ Never use running water or immerse the charger in water.
- ▶ Do not sterilize or disinfect the charger.



## **Professional maintenance**

Your Hearing Care Professional can perform a thorough professional cleaning and maintenance.

Ask your Hearing Care Professional for your individual recommendation of maintenance intervals and for support.

# Important safety information for hearing instruments and charger

## Safety information on lithium-ion rechargeable batteries



### **WARNING**

A lithium-ion rechargeable battery is permanently built into your device. Incorrect use of the device can cause the lithium-ion rechargeable battery to burst.

Risk of injury, fire or explosion!

- ▶ Follow the safety instructions for lithium-ion rechargeable battery in this section.

- Observe the operating conditions. Refer to the section "Operating, transport, and storage conditions".
- Pay special attention to protect your device from extreme heat (e.g. fire, microwave oven, induction oven or other high induction fields) and sunlight.
- Charge your hearing instruments only with the approved charger. Ask your Hearing Care Professional for support.
- Do not disassemble the device.
- Do not use the device in explosive atmospheres.
- Do not use devices that are deformed or obviously damaged.

- Do not use the device when its performance after charging decreases considerably. Return the device to your Hearing Care Professional.
- Do not dispose of the device in fire or water.

Replacement and repair have to be performed by a professional. Therefore:

- Do not repair or replace the lithium-ion rechargeable battery yourself.
- In the unlikely event of a lithium-ion rechargeable battery bursting or exploding, keep all combustible materials away.

In any of the above cases, return your device to the Hearing Care Professional.



### **WARNING**

Risk of electric shock!

- ▶ Connect the charger only with a USB power supply which complies with IEC 60950-1 and/or IEC62368-1.

### **Safety information for hearing instruments**

For more safety information, refer to the safety manual supplied with the device.

## Safety information for charger

### Personal safety for charger



#### **WARNING**

Risk of electrical shock!

- ▶ Do not use obviously damaged devices and return them to point of sale.



#### **WARNING**

Risk of injury!

- ▶ Do not use obviously damaged devices and return them to point of sale.



#### **WARNING**

Note that any unauthorized changes to the product may cause damage to the product or cause injury.

- ▶ Use only approved parts and accessories.  
Ask your Hearing Care Professional for support.



#### **WARNING**

Risk of explosion!

- ▶ Do not use your device in explosive atmospheres (e.g. in mining areas).



#### **WARNING**

Risk of burns!

- ▶ Do not place anything other than your hearing instruments in the charger.



## **WARNING**

Choking hazard!

Your device contains small parts which can be swallowed.

- ▶ Keep hearing instruments, batteries and accessories out of reach of children and mentally disabled persons.
- ▶ If parts have been swallowed consult a physician or hospital immediately.



## **WARNING**

Charging systems may interfere with measuring devices and electronic equipment.

- ▶ In hospitals: The charger complies with CISPR 35 and CISPR 32. Therefore the use of the charger in hospitals should be permissible. Nevertheless the charger may interfere with highly sensitive devices. In those cases appropriate steps shall be taken (increase distance from sensitive devices or disconnect the charger from power supply).



## **WARNING**

### Interference with implantable devices

- ▶ The device can be used with all electronic implants that comply with the ANSI/AAMI/ISO 14117:2012 Electromagnetic compatibility standard for human implants.
- ▶ In case your implant does not comply with the ANSI/AAMI/ISO 14117:2012 standard, consult the manufacturer of your implantable device for information about the risk of disturbance.

## Product safety for charger



### **NOTICE**

- ▶ Protect your device from extreme heat. Do not store it in direct sunlight.



### **NOTICE**

- ▶ Protect your devices from high humidity.



### **NOTICE**

- ▶ Do not dry your devices in the microwave oven.



### **NOTICE**

- ▶ Do not drop. Internal components may get damaged.

## Requirements for the electrical plug

Use an electrical plug with an output voltage of 5 V and a maximum output current of 500 mA.



### **WARNING**

Risk of electric shock!

- ▶ Connect the charger only with a USB power supply which complies with IEC 60950-1 and/or IEC62368-1.

## Further information

### Accessories

The type of available accessories depends on the instrument type. Examples are: a remote control, an audio streaming device, or a smartphone app for remote control.

Some hearing instrument types support CROS and BiCROS solutions for people with single-sided deafness.

Consult your Hearing Care Professional for further information.

### Operating, transport and storage conditions for hearing instruments and charger

Operating conditions	Discharging	Charging
Temperature	0 to 50 °C (32 to 122 °F)	10 to 35 °C (50 to 95 °F)
Relative humidity	5 to 93 %	20 to 75 %
Atmospheric pressure	700 to 1060 hPa	700 to 1060 hPa



During extended periods of transport and storage, please observe the following conditions:

	Storage	Transport
Temperature (recommended)	10 to 25 °C (50 to 77 °F)	-20 to 60 °C (-4 to 140 °F)
Temperature (maximum range)	10 to 40 °C (50 to 104 °F)	-20 to 60 °C (-4 to 140 °F)
Relative humidity (recommended)	20 to 80 %	5 to 90 %
Relative humidity (maximum range)	10 to 80 %	5 to 90 %
Atmospheric pressure	700 to 1060 hPa	700 to 1060 hPa

Note that you have to charge the hearing instruments at least every 6 months. For details refer to section "Maintenance and care".



#### **WARNING**

Risk of injury, fire or explosion during shipment.

- ▶ Ship power cells, hearing instruments and/or charger according to local regulations

#### **Disposal information**

- ▶ To avoid environmental pollution, do not throw power cells, hearing instruments or charger into household trash.
- ▶ Recycle or dispose of power cells, hearing instruments or charger according to local regulations.

## Symbols

### Symbols used in this document



Points out a situation that could lead to serious, moderate, or minor injuries.



Indicates possible property damage.



Advice and tips on how to handle your device better.



Frequently asked question.

Made for

iPhone | iPad | iPod

“Made for iPhone”, “Made for iPad”, and “Made for iPod” mean that an electronic accessory has been designed to connect specifically to iPhone, iPad, or iPod, respectively, and has been certified by the developer to meet Apple performance standards. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPhone, iPad, or iPod may affect wireless performance.

## Symbols on the device or packaging



CE compliance label, confirms compliance with certain European Directives, refer to section "Conformance information".

---



Indicates the legal manufacturer of the device.

---



Do not dispose of the device with general domestic waste. Read more in section "Disposal information".

---



Read and follow the instructions in the user guide.

---

## Troubleshooting

### Problem and possible solutions

Sound is weak.

- Increase the volume.
- Charge the hearing instrument.
- Clean or exchange the ear piece.

Hearing instrument emits whistling sounds.

- Reinsert the ear piece until it fits securely.
- Decrease the volume.
- Clean or exchange the ear piece.

Sound is distorted.

- Decrease the volume.
- Charge the hearing instrument.
- Clean or exchange the ear piece.

Hearing instrument emits signal tones.

- Charge the hearing instrument.

Hearing instrument does not work.

- Turn the hearing instrument on.
- Charge the hearing instrument.  
Observe also the status LEDs on the charger.

Consult your Hearing Care Professional if you encounter further problems.

## Country-specific information

### USA and Canada

Certification information for hearing instruments with wireless functionality:

Adore StyleLine BT:

- HVIN: WP4N1
- Contains FCC ID: SGI-RFM001
- IC: 267AB-WP4N1

## Important information

### Conformance information for charger

The CE mark indicates conformity with the following European directives:



- 2014/30/EU concerning electromagnetic compatibility
- 2014/35/EU concerning electrical equipment designed for use within certain voltage limits
- 2011/65/EU RoHS concerning the restriction of hazardous substances

The CE mark indicates conformity with certain European directives. The full text of the declaration of conformity can be obtained from [www.sivantos.com/doc](http://www.sivantos.com/doc).

This device complies with Part 15 of the FCC Rules and with Canadian license-exempt RSS standard(s).

Operation is subject to the following two conditions:

- This device may not cause harmful interference, and
- this device must accept any interference received, including interference that may cause undesired operation.

For conformance information for hearing instruments, refer to the safety manual supplied with the device.

## Service and warranty

### Serial numbers

Left hearing instrument:

Right hearing instrument:

Charger:

### Service dates

1:

4:

2:

5:

3:

6:

### Warranty

Date of purchase:

Warranty period in months:

Your Hearing Care Professional

 **Legal Manufacturer:**

**hearing instrument**

Sivantos GmbH

Henri-Dunant-Strasse 100

91058 Erlangen

Germany

Phone +49 9131 308 0

  
0123

 **Legal Manufacturer:**

**charger**

Sivantos GmbH

Henri-Dunant-Strasse 100

91058 Erlangen

Germany

Phone +49 9131 308 0



**only for Adore StyleLine BT:**

Made for



**iPhone | iPad | iPod**

Document No. 03931-99T01-7600 EN

Order/Item No. 109 667 90

Master Rev03, 05.2019

© 05.2019, Sivantos GmbH. All rights reserved

[www.rexton.com](http://www.rexton.com)

**REXTON** 